

NEMA 4X CONTROL PANELS 1,2,3
GRINDER PUMPS, 2 - 7½ HP
SINGLE DIRECTIONAL

PUMP DATA						SIMPLEX			DUPLEX		
Model Number	BHP	Voltage	Phase	Full Load Amps	Panel Amp Range	Part Number	*Weight (lbs.)	*Dimensions H x W x D	Part Number	*Weight (lbs.)	*Dimensions H x W x D
E6842	2	230	1	17.2	15.0-20.0	10-1650	15	14" x 12" x 6"	10-1652	22	18" x 16" x 8"
I6842	2	200	1	20.0	15.0-20.0	10-1650	15	14" x 12" x 6"	10-1652	22	18" x 16" x 8"
J6842	2	200	3	12.3	9.0-14.0	10-1097	18	12" x 10" x 6"	10-1125	22	16" x 14" x 6"
F6842	2	230	3	10.8	9.0-14.0	10-1097	18	12" x 10" x 6"	10-1125	22	16" x 14" x 6"
G6842	2	460	3	5.5	4.0-6.3	10-1094	18	12" x 10" x 6"	10-1122	22	16" x 14" x 6"
BA6842	2	575	3	4.5	4.0-6.3	10-1146	18	12" x 10" x 6"	10-1168	22	16" x 14" x 6"
E6841	3	230	1	17.2	15.0-20.0	10-1650	15	14" x 12" x 6"	10-1652	22	18" x 16" x 8"
I6841	3	200	1	20.0	15.0-20.0	10-1650	15	14" x 12" x 6"	10-1652	22	18" x 16" x 8"
J6841	3	200	3	12.3	9.0-14.0	10-1097	18	12" x 10" x 6"	10-1125	22	16" x 14" x 6"
F6841	3	230	3	10.8	9.0-14.0	10-1097	18	12" x 10" x 6"	10-1125	22	16" x 14" x 6"
G6841	3	460	3	5.5	4.0-6.3	10-1094	18	12" x 10" x 6"	10-1122	22	16" x 14" x 6"
BA6841	3	575	3	4.5	4.0-6.3	10-1146	18	12" x 10" x 6"	10-1168	22	16" x 14" x 6"
E7110	3	230	1	23.6	21.0-30.0	10-1309	27	14" x 12" x 6"	10-1310	45	18" x 16" x 9"
J7110	3	200	3	17.3	17.0-23.0	10-1100	18	12" x 10" x 6"	10-1128	22	16" x 14" x 6"
F7110	3	230	3	15.1	13.0-18.0	10-1098	18	12" x 10" x 6"	10-1126	22	16" x 14" x 6"
G7110	3	460	3	7.5	6.0-10.0	10-1096	18	12" x 10" x 6"	10-1124	22	16" x 14" x 6"
BA7110	3	575	3	6.0	4.0-6.3	10-1146	18	12" x 10" x 6"	10-1168	22	16" x 14" x 6"
E7111	5	230	1	28.0	25.0-30.0	10-0963	27	14" x 12" x 6"	10-0968	45	18" x 16" x 9"
J7111	5	200	3	20.7	20.0-25.0	10-1101	18	12" x 10" x 6"	10-1129	22	16" x 14" x 6"
F7111	5	230	3	18.0	17.0-23.0	10-1100	18	12" x 10" x 6"	10-1128	22	16" x 14" x 6"
G7111	5	460	3	9.0	9.0-14.0	10-1097	18	12" x 10" x 6"	10-1125	22	16" x 14" x 6"
BA7111	5	575	3	7.2	6.0-10.0	10-1148	18	12" x 10" x 6"	10-1170	22	16" x 14" x 6"
J7112	7-1/2	200	3	25.3	23.0-32.0	10-1177	21	18" x 16" x 6"	10-1186	30	28" x 20" x 9"
F7112	7-1/2	230	3	22.0	20.0-25.0	10-1101	21	18" x 16" x 6"	10-1129	22	28" x 20" x 9"
G7112	7-1/2	460	3	11.0	9.0-14.0	10-1097	18	12" x 10" x 6"	10-1125	22	16" x 14" x 6"
BA7112	7-1/2	575	3	9.0	9.0-14.0	10-1149	18	12" x 10" x 6"	10-1171	22	16" x 14" x 6"

INTRINSICALLY SAFE FOR EXPLOSION PROOF X71 SERIES GRINDER PUMPS, 3 - 7½ BHP

PUMP DATA						SIMPLEX			DUPLEX		
Model Number	BHP	Voltage	Phase	Full Load Amps	Panel Amp Range	Part Number	*Weight (lbs.)	*Dimensions H x W x D	Part Number	*Weight (lbs.)	*Dimensions H x W x D
EX7110	3	230	1	23.6	23.0-32.0	10-1574	25	16" x 14" x 6"	10-1602	35	28" x 20" x 10"
JX7110	3	200	3	17.3	17.0-23.0	10-1570	25	16" x 14" x 6"	10-1598	25	16" x 14" x 6"
FX7110	3	230	3	15.1	13.0-18.0	10-1571	25	16" x 14" x 6"	10-1599	25	16" x 14" x 6"
GX7110	3	460	3	7.5	6.0-10.0	10-1565	25	16" x 14" x 6"	10-1593	25	16" x 14" x 6"
BAX7110	3	575	3	6.0	6.0-10.0	10-1572	25	16" x 14" x 6"	10-1600	25	16" x 14" x 6"
EX7111	5	230	1	28.0	23.0-32.0	10-1574	25	16" x 14" x 6"	10-1602	35	28" x 20" x 10"
JX7111	5	200	3	20.7	17.0-23.0	10-1570	25	16" x 14" x 6"	10-1598	25	16" x 14" x 6"
FX7111	5	230	3	18.0	17.0-23.0	10-1570	25	16" x 14" x 6"	10-1598	25	16" x 14" x 6"
GX7111	5	460	3	9.0	9.0-14.0	10-1568	25	16" x 14" x 6"	10-1596	25	16" x 14" x 6"
BAX7111	5	575	3	7.2	6.0-10.0	10-1572	25	16" x 14" x 6"	10-1600	25	16" x 14" x 6"
JX7112	7-1/2	200	3	25.3	23.0-32.0	10-1577	27	18" x 16" x 6"	10-1605	35	28" x 20" x 10"
FX7112	7-1/2	230	3	22.0	17.0-23.0	10-1570	25	16" x 14" x 6"	10-1598	25	16" x 14" x 6"
GX7112	7-1/2	460	3	11.0	9.0-14.0	10-1568	25	16" x 14" x 6"	10-1596	25	16" x 14" x 6"
BAX7112	7-1/2	575	3	9.0	9.0-14.0	10-1576	25	16" x 14" x 6"	10-1604	25	16" x 14" x 6"

- NOTES:** (1) Single phase panels have starting capacitors and relays mounted in the enclosure. Therefore, these panels can only be used with Zoeller pumps.
(2) Three phase panels up to 20-25 amps have multi-tap transformers for 200-230-460 volt applications and are selected based on pump features and rated full load amps (FLA).
(3) The above listed panels meet our standard configurations. If any standard or nonstandard options are required, consult factory.
*Weights and dimensions are approximations and could vary.



www.zoeller.com



MAIL TO: P.O. BOX 16347
Louisville, KY 40256-0347
SHIP TO: 3649 Cane Run Road
Louisville, KY 40211-1961
(502) 778-2731 • 1 (800) 928-PUMP
FAX (502) 774-3624

Manufacturers of . .

QUALITY PUMPS SINCE 1939